



# Panasonic

[Products](#)[Business](#)[Promotions](#)[News](#)[Blogs](#)[e-shop](#)[My Panasonic](#)[Support](#)

## KX-TG6852 digital cordless telephone

### General

**Color**

N [Black]

**Cordless handset (quantity)**

2

**Standard cordless telephone****Standard cordless telephone**

DECT, GAP

**DECT security mode**

Yes (not certified)

<b>Number of telephone lines</b>	1
<b>Multiple cordless handset functionality</b>	Up to 6 receivers

<b>Other communication standard</b>	<b>Wi-Fi®</b>	-
	<b>Bluetooth® class</b>	-

## Eco function

<b>Eco mode</b>	Yes
<b>Without radiation</b>	Yes (ECO Plus mode)

## Practical

<b>Connection to smartphone</b>	-	
<b>Repeater available</b>	Yes	
<b>Call blocking by number</b>	<b>Call barring (blocking specific numbers)</b>	Yes (1000 numbers) *1, *2
	<b>Nuisance Call Blocking (Blocking Number Ranges)</b>	Yes *1



	<b>Blocking calls with hidden number</b>	Yes *1, *3
	<b>Easy registration via Call Block button (cordless handset)</b>	Yes
	<b>Easy registration via Call Block button (base unit)</b>	-
<b>Automatic call blocking</b>	<b>Automatic call blocking</b>	-
	<b>Allow number database</b>	-
	<b>Allow name list</b>	-
	<b>Language of the pre-recorded greeting</b>	-
<b>Noise reduction</b>	<b>Cordless handset</b>	Yes
	<b>Response system</b>	-
<b>Custom sound system (equalizer)</b>	Yes (Treble/Treble/Bass)	
<b>HAC (Hearing Aid Compatibility) support</b>	-	

**Emergency power operation**

-

**Operation in the event of a power failure**

-

**Low battery sound warning**

Yes

**Baby Monitor function**

Yes

**Smart function key**

-

**Smart ringer (cordless handset)**

-

**Answer with any key**

Yes

**Do not disturb mode****Do not disturb mode**

Yes

**Option to bypass Do Not Disturb mode (specified address book category)**

Yes \*1

**SMS**

-

**Talking keys**

-

**Call restriction**

Yes



<b>Emergency call</b>	<b>Emergency call</b>	-
	<b>Number of emergency lists</b>	-
<b>Conference call</b>	<b>Conference call with external line</b>	Yes, 3-way *5
	<b>Call sharing</b>	Yes
	<b>Call sharing notification</b>	Yes (display and tone)
<b>Call via intercom</b>	<b>Between cordless handset and base unit</b>	-
	<b>Between cordless handsets</b>	Yes
	<b>Intercom All</b>	Yes (to all handsets) *4
	<b>Voice pager</b>	Yes
<b>Clock</b>		Yes
<b>Alarm</b>	<b>Alarm</b>	Yes
	<b>Repeat option</b>	Once/Every day/Every week
	<b>Memo alarm</b>	Yes



---

<b>Snooze</b>	Yes
---------------	-----

---

<b>Bluetooth headphone function (HSP support)</b>	-
---	---

---

## Caller ID

---

<b>Caller ID</b>	Yes *1
------------------	--------

---

<b>Caller ID memory</b>	50 items *1
-------------------------	-------------

---

<b>Caller ID call waiting</b>	Yes *6
-------------------------------	--------

---

<b>Ringtone category</b>	Yes *1, *7
--------------------------	------------

---

<b>Private ringtone</b>	-
-------------------------	---

---

<b>Category display colors</b>	-
--------------------------------	---

---

<b>Caller name ID</b>	<b>Cordless handset</b>	-
-----------------------	-------------------------	---

---

	<b>Basic unit</b>	-
--	-------------------	---

---

	<b>Advertisement language</b>	-
--	-------------------------------	---

---



## Address book

---

<b>Phonebook memory (name/number)</b>	200 elements (16 characters/24 digits)
---	--

---

<b>Shared address book</b>	Yes
----------------------------	-----

---

<b>Copying the phonebook (from cordless handset to cordless handset)</b>	-
--	---

---

<b>Copying the phonebook from a mobile phone via Bluetooth</b>	-
--	---

---

<b>Speed dial</b>	<b>Cordless handset</b>	-
-------------------	-------------------------	---

---

<b>Basic unit</b>	-
-------------------	---

---

<b>Quick calls</b>	<b>Cordless handset</b>	Yes (9 items)
--------------------	-------------------------	---------------

---

<b>Basic unit</b>	-
-------------------	---

---

<b>Chained selection</b>	<b>Cordless handset</b>	Yes
--------------------------	-------------------------	-----

---

<b>Basic unit</b>	-
-------------------	---

---

## Compatibility with FRITZ!BOX

---

**Compatibility with FRITZ!BOX** -

---

**Using the FRITZ!Box address book** -

---

**Caller ID indicator (name/number)** -

---

## Cordless handset

---

<b>Display</b>	<b>Guy</b>	Monochrome LCD 103 x 65 pixels
	<b>Dimensions diagonally</b>	4.5cm
	<b>Tongue</b>	English, German, Spanish, Norwegian, French, Italian, Danish, Dutch, Swedish, Finnish, Greek, Turkish, Portuguese, Catalan
	<b>Full color backlit</b>	White
<b>Key/Button</b>	<b>Illuminated keypad</b>	Yes (amber)
	<b>Short key stroke</b>	Yes
	<b>Call blocking</b>	Yes
	<b>Key lock</b>	Yes





	<b>Lateral volume</b>	-
	<b>Amplified volume button</b>	-
<b>Resistente agli urti</b>	<b>Resistente agli urti</b>	-
	<b>Standard di test</b>	-
<b>Volume ricevitore</b>	<b>Livelli volume</b>	4 fasi
	<b>Volume alto</b>	-
<b>Vivavoce</b>	<b>Vivavoce</b>	Si
	<b>Full Duplex</b>	Si
	<b>Livelli volume</b>	6 fasi
	<b>Volume alto</b>	-
<b>Suoneria</b>	<b>Suoneria</b>	40
	<b>Livelli volume</b>	6 fasi + OFF
<b>Ricomposizione</b>	<b>Memoria per la ricomposizione</b>	10 (nome e numero) *8
	<b>Ricomposizione automatica</b>	-



<b>Indicatore</b>	<b>Indicatore suoneria (colore)</b>	-
	<b>Indicatore carica (colore)</b>	-
	<b>Indicatore chiamante sconosciuto</b>	Sì (tasto blocco chiamate)
<b>Blocco tasti</b>	<b>Blocco tasti</b>	Sì
	<b>Protezione con password</b>	Sì
<b>Attesa</b>		Sì
<b>Silenzioso</b>		Sì
<b>Jack per cuffie</b>		-
<b>Montaggio a parete (caricatore)</b>		-
<b>Batteria</b>	<b>Tipo</b>	Ricaricabile - Ni-MH
	<b>Quantità x Dimensioni</b>	2 x AAA
	<b>Autonomia di conversazione</b>	Fino a 18 ore *9
	<b>Autonomia in standby</b>	Fino a 200 ore *9



---

<b>Tempo di ricarica</b>	Circa 7 ore
--------------------------	-------------

---

## Unità base

---

<b>Ricevitore con filo</b>	-
----------------------------	---

---

<b>Display</b>	<b>Tipo</b>	-
	<b>Dimensioni in diagonale</b>	-
	<b>Lingua</b>	-
	<b>A colori retroilluminato</b>	-

---

<b>Tasto/Pulsante</b>	<b>Tastierino</b>	-
	<b>Ricerca ricevitore</b>	Si
	<b>Ricerca cellulare</b>	-

---

<b>Vivavoce</b>	<b>Vivavoce</b>	-
	<b>Livelli volume</b>	-
	<b>Volume alto</b>	-

---



---

**Suoneria****Suoneria**

-

---

**Livelli volume**

-

---

**Ricomposizione****Memoria per la ricomposizione**

-

---

**Ricomposizione automatica**

-

---

**Attesa**

-

---

**Silenzioso**

-

---

**Possibilità di montaggio a parete**

-

---

**Sistema di risposta**

---

**Sistema di risposta**

-

---

**Lingua del messaggio di saluto  
preregistrato**

-

---

**Durata totale registrazione**

-

---

**Avanzamento e arretramento  
rapido dei messaggi**

-



**Avviso messaggi acustico**

-

**Notifica nuovo messaggio****Tipo di notifica**

-

**Lingua di annuncio della notifica di nuovi messaggi**

-

**Registrazione conversazione**

-

**Livelli volume altoparlante (altoparlante dell'unità base)**

-

**Selezione chiamate****Ricevitore cordless**

-

**Unità base**

-

**Accesso remoto****Funzionamento da ricevitore cordless**

-

**Funzionamento dall'esterno (DTMF)**

-

**Risparmio tariffa****Risparmio tariffa**

-

**Nuovi messaggi registrati**

-



## Accessori

---

Ripetitore incluso -

---

Clip per cintura incluso -

---

## Consumo energetico

---

Consumo energetico in standby dell'unità base 0,6 W

---

Consumo energetico in standby del caricatore 0,2 W

---

## Ricevitore opzionale

---

Ricevitore opzionale Sì (KX-TGA685)

---

## Dimensioni / Peso

---

Unità base	<b>Dimensioni (A x L x P)</b>	Circa 77 mm x 107 mm x 86 mm
	<b>Peso</b>	Circa 100 g

---

Ricevitore cordless	<b>Dimensioni (A x L x P)</b>	Circa 164 mm x 48 mm x 29 mm
---------------------	-------------------------------	------------------------------

---



	<b>Peso con batteria</b>	circa 130 g
<b>Caricabatteria</b>	<b>Dimensioni (A x L x P)</b>	Circa 39 mm x 70 mm x 70 mm
	<b>Peso</b>	Circa 40 g
<b>Ripetitore</b>	<b>Dimensioni (A x L x P)</b>	-
	<b>Peso</b>	-

## Nota

- \*1 Richiede la sottoscrizione al servizio ID chiamante offerto dal gestore o dall'operatore telefonico.
- \*2 Richiede la registrazione del numero nell'elenco blocco chiamate indesiderate.
- \*3 Potrebbe non essere possibile bloccare le chiamate con numero nascosto, a seconda del servizio offerto dall'operatore telefonico.
- \*4 Richiede il ricevitore opzionale.
- \*5 3 vie: Ricevitore cordless - Ricevitore cordless - Linea fissa
- \*6 Richiede la sottoscrizione del servizio identificativo del chiamante e al servizio di chiamata in attesa con identificativo del chiamante offerti dall'operatore telefonico.
- \*7 Richiede la registrazione nella funzione Rubrica.
- \*8 La visualizzazione del nome richiede la registrazione nella rubrica.
- \*9 Le prestazioni effettive della batteria dipendono dall'utilizzo e dal tipo di ambiente.



